

**Energy Division** 

Raychem screened, separable connection system RSTI-68 800 A up to 42 kV



# Raychem screened, separable connection system RSTI-68, 800 A up to 42 kV



#### Features

- The insulation of the connector is made of a highly modified silicone rubber characterised by high tracking resistance, elongation at break and non-flammability.
- A thin walled screen is permanently bonded onto the insulation and protects the connection system against accidental contact.
- The screened connector need not be removed for over sheath testing.
- The screened cable connector exceeds CENELEC HD 629.1 S2 requirements, which includes BS; VDE and other international specifications.
- Design fits 630 A and 1250 A bushings (Interface "C1" and "C2") as specified by EN 50180 and EN 50181.
- The compact design supports the use of double "T" connections inside standard terminal boxes.
- The wide application range covers cable cross sections from 35 to 300 mm<sup>2</sup>.
- Conductor connection with mechanical, DIN or deep indent lugs.
- Easily accessible rear plug with capacitive test point.
- Few accessories required for system test, double "T" and earth connection.
- Complete kit including lugs facilitates installation and storage.

Raychem RSTI screened separable connectors are designed to connect single- and three-core polymeric cables to medium-voltage gas insulated switchgear and other equipment using CENELEC bushings Type  $C_1$ =630 A and  $C_2$ =1250 A, specified up to 42 kV.


Made of a highly modified silicone rubber and protected by a thin walled outer conductive screen connected to earth, RSTI connectors are equally suited for indoor and outdoor installation.

Supporting a wide application range, the design incorporates one body and two stress cone adapters to cover all cross-sections from 35 to 300 mm<sup>2</sup>. The overall and cut back dimensions are designed to take up minimum space in the terminal box. RSTI connectors are equipped with a capacitive test point for determining whether the circuit is energised. A conductive cap protects this test point.

## Applications

#### Single connection

Material requested for 3 phases: 1 x RSTI-68xx (Kit)



## Accessories

#### Test rod

Ref. no.: RSTI-68TR; Length: 310 mm RSTI-68TRL; Length: 460 mm RSTI-68TRA; Kit includes 2 short and 1 long testrod



#### Terminating plug Ref. no.: RSTI-68TP




Earthing adapter Ref. no.: RSTI-68EA20; Ball diameter: 20 mm RSTI-68EA25; Ball diameter: 25 mm




### Live end seal

Material requested for 3 phases: 1 x RSTI-68xx (Kit) 1 x RSTI-68TP (Terminating plug kit)



**Design and construction** 



Note: All applications as shown in the brochure need to have a mechanical support, based on the requirements for dynamic short circuit.

## 1 Screened body

A thin walled conductive outer screen is permanently bonded to the silicone rubber insulating material of the body.

#### 2 Inner screen

A conductive inner layer, as a Faraday cage around the compression or mechanical lug, prevents corona at rated voltage.

### **3** Compression or mechanical lugs

Specially designed DIN and deep indent compression lugs, as well as tinned, mechanical lugs with shear bolts for connecting either aluminium or copper conductor cables.

## 4 Stress cone adapter

Relieves electrical stress at the point where the cable screen is cut. The insulated section, extending beyond the wire shielding, provides a convenient point for over sheath testing.

#### 5 Earthing eye and ground lead

Provides a connection point for earthing the screen.

## 6 Threaded pin

A threaded pin together with a spring washer (wave type) and hex nut ensure a high performance electrical and mechanical contact with the bushing.

#### 7 Rear plug with test point

Removable rear plug with capacitive test point.

## 8 Test point


The test point is used to determine whether the circuit is energised; alternatively it can be used for phasing.

#### 9 Conductive end cap

Electrical screen and protection of the rear end of the separable connector.

### Mechanical lug

Compression lug



# Raychem screened, separable connection system RSTI-68, 800 A up to 42 kV

Technical data	Cable insulation diameter range	22.4 - 42.0 mm	
	Connector cross-section range	35 - 300 mm² 42 kV	
	Maximum system voltage		
	Continuous current rating	800 A	
	Basic impulse level	200 kV	
	Partial discharge at 2 $U_0$	< 2 pC	
	AC voltage withstand, 5 min	93.5 kV	
	DC voltage withstand, 15 min	125 kV	
	Thermal short circuit, 1 s	55 kA	
	Thermal short circuit, 3 s	32 kA	
	Dynamic short circuit	125 kA	
	The adapters meet the international CENELEC HD 629.1 S2 specification		

#### Selection table

## Screened separable connection system 36 kV and 42 kV with DIN compression lugs

Diameter Reference number Core insulation		Conductor material	
min	max	AI	Cu
22.4 -	35.5	RSTI-6811	RSTI-6821
22.4 -	35.5	RSTI-6812	RSTI-6822
22.4 -	35.5	RSTI-6813	RSTI-6823
22.4 -	35.5	RSTI-6814	RSTI-6824
28.9 -	42.0	RSTI-6815	RSTI-6825
28.9 -	42.0	RSTI-6816	RSTI-6826
28.9 -	42.0	RSTI-6817	RSTI-6827
28.9 -	42.0	RSTI-6818	RSTI-6828
	Core in min mm 22.4 - 22.4 - 22.4 - 22.4 - 22.4 - 28.9 - 28.9 - 28.9 - 28.9 -	Core insulation min max mm   22.4 - 35.5   22.4 - 35.5   22.4 - 35.5   22.4 - 35.5   22.4 - 35.5   22.4 - 35.5   22.4 - 35.5   22.4 - 35.5   28.9 - 42.0   28.9 - 42.0   28.9 - 42.0	Core insulation max Conductor material Al   min max Al   22.4 35.5 RSTI-6811   22.4 - 35.5 RSTI-6812   22.4 - 35.5 RSTI-6813   22.4 - 35.5 RSTI-6813   22.4 - 35.5 RSTI-6813   22.4 - 35.5 RSTI-6814   28.9 - 42.0 RSTI-6815   28.9 - 42.0 RSTI-6816   28.9 - 42.0 RSTI-6817

Kits with deep indent compression lugs on request. Contact your local sales representative.

#### Screened separable connection system 36 kV and 42 kV with mechanical lugs and shear bolts

Cross Section	Diameter Reference number Core insulation min max		r Conductor material Al or Cu	
mm <sup>2</sup>	mm	mm		
35 - 95	22.4 -	35.5	RSTI-6851	
95 - 150	22.4 -	35.5	RSTI-6852	
120 - 240	28.9 -	42.0	RSTI-6853	
185 - 300	28.9 -	42.0	RSTI-6855	

Kits for 3-core applications on request. Contact your local sales representative

While Tyco Electronics and its affiliates referenced herein have made every reasonable effort to ensure the accuracy of the information contained in this catalog, Tyco Electronics cannot assure that this information is error free. For this reason, Tyco Electronics does not make any representation or offer any guarantee that such information is accurate, correct, reliable or current. Tyco Electronics reserves the right to make any adjustments to the information at any time. Tyco Electronics expressly disclaims any implied warranty regarding the information or offer any guarantee that such information is accurate, correct, reliable or current. Tyco Electronics reserves the right to the implied warranties of merchantability or fitness for a particular purpose. Tyco Electronics only obligations are those stated in Tyco Electronics' Standard Terms and Conditions of Sale. Tyco Electronics will in no case be liable for any incidental, indirect or consequential damages arising from or in connection with, including, but not limited to, the implication. User should rely on their own judgement to evaluate the suitability of a product for a certain purpose and test each product for its intended application. In case of any potential ambiguities or questions, please don't hesitate to contact us for clarification. Raychem, TE (logo) and Tyco Electronics are trademarks of the Tyco Electronics are trademarks of the

Energy Division – innovative and economical solutions for the electrical power industry: cable accessories, connectors & fittings, insulators & insulation, surge arresters, switching equipment, lighting controls, power measurement and control.

Tyco Electronics Raychem GmbH Energy Division Finsinger Feld 1 85521 Ottobrunn/Munich, Germany

Phone: +49-89-6089-0 Fax: +49-89-6096345



http://energy.tycoelectronics.com